Point Safe Electronic Series

OPERATING INSTRUCTIONS
(HOTEL MODE)



www.burgsecurity.com.au

CONVERTING SAFE TO HOTEL MODE

- Open the safe door - with the door open press the [CLOSE] button so that the locking bars are extended (out of door).
- Press [ENTER] – “CODE” appears in display.
- Enter **master code (pre-selected 1-2-3-4-5-6-7-8**) and press [ENTER] again.
- “PASS 1, PASS 2, PASS 3 … PASS 0” appears in display.
- **Before** this count is finished press [ENTER] again - “CODE” appears in display.
- Enter the code “16805” and press [ENTER] – “SET-05” appears in display.


In “Hotel” mode if the door remains open for more than 5 minutes, a user code has to be entered again.

CONVERTING SAFE TO HOME MODE

- Open the safe door - with the door open press the [CLOSE] button so that the locking bars are extended (out of door).
- Press [ENTER] – “CODE” appears in display.
- Enter **master code (pre-selected 1-2-3-4-5-6-7-8**) and press [ENTER] again.
- “PASS 1, PASS 2, PASS 3 … PASS 0” appears in display.
- **Before** this count is finished press [ENTER] again - “CODE” appears in display.
- Enter the code “16800” and press [ENTER] – “SET-00” appears in display.

In “Home” mode the user code will not reset even if the door is left opened.

Set Code



1 - Enter
2 - Code (xxxx)
3 - Enter
4 - Close



Open Safe



1 - Enter
2 - Code (xxxx)
3 - Enter



On departure:
Please leave safe door open



Thank you